



SIRIUS soft starter 200-600 V 38 A, 24 V AC/DC spring-type terminals  
Analog output

|  |   |
|--|---|
| product brand name                               | SIRIUS  |
| product category                                 | Hybrid switching devices  |
| product designation                              | Soft starter  |
| product type designation                         | 3RW52   |
| manufacturer's article number                    | <ul style="list-style-type: none"><li>• of standard HMI module usable</li><li>• of high feature HMI module usable</li><li>• of communication module PROFINET standard usable</li><li>• of communication module PROFIBUS usable</li><li>• of communication module Modbus TCP usable</li><li>• of communication module Modbus RTU usable</li><li>• of communication module Ethernet/IP</li><li>• of circuit breaker usable at 400 V</li><li>• of circuit breaker usable at 500 V</li><li>• of circuit breaker usable at 400 V at inside-delta circuit</li><li>• of circuit breaker usable at 500 V at inside-delta circuit</li><li>• of the gG fuse usable up to 690 V</li><li>• of the gG fuse usable at inside-delta circuit up to 500 V</li><li>• of full range R fuse link for semiconductor protection usable up to 690 V</li><li>• of back-up R fuse link for semiconductor protection usable up to 690 V</li></ul> |
| General technical data                           |   |
| starting voltage [%]                             | 30 ... 100 %  |
| stopping voltage [%]                             | 50 ... 50 %   |
| start-up ramp time of soft starter               | 0 ... 20 s  |
| current limiting value [%] adjustable            | 130 ... 700 %   |
| certificate of suitability                       | <ul style="list-style-type: none"><li>• CE marking</li><li>• UL approval</li><li>• CSA approval</li></ul>   |
| product component is supported                   | <ul style="list-style-type: none"><li>• HMI-Standard</li><li>• HMI-High Feature</li></ul>   |
| product feature integrated bypass contact system |   |












|   |
|---|
| 3RW5980-0HS00   |
| 3RW5980-0HF00   |
| 3RW5980-0CS00   |
| 3RW5980-0CP00   |
| 3RW5980-0CT00   |
| 3RW5980-0CR00   |
| 3RW5980-0CE00   |
| 3RV2032-4WA10: Type of coordination 1, Iq = 65 kA, CLASS 10 |
| 3RV2032-4WA10: Type of coordination 1, Iq = 10 kA, CLASS 10 |
| 3RV2032-4RA10: Type of coordination 1, Iq = 65 kA, CLASS 10 |
| 3RV2032-4RA10: Type of coordination 1, Iq = 10 kA, CLASS 10 |
| 3NA3824-6: Type of coordination 1, Iq = 65 kA               |
| 3NA3824-6: Type of coordination 1, Iq = 65 kA               |
| 3NE1820-0: Type of coordination 2, Iq = 65 kA               |
| 3NE8024-1: Type of coordination 2, Iq = 65 kA               |

|   |   |
|---|---|
| <b>number of controlled phases</b>  | 3   |
| <b>trip class</b>   | CLASS 10A (default) / 10E / 20E; acc. to IEC 60947-4-2                          |
| <b>buffering time in the event of power failure</b>                                 |   |
| • for main current circuit  | 100 ms  |
| • for control circuit   | 100 ms  |
| <b>insulation voltage rated value</b>   | 600 V   |
| <b>degree of pollution</b>  | 3, acc. to IEC 60947-4-2  |
| <b>impulse voltage rated value</b>  | 6 kV  |
| <b>blocking voltage of the thyristor maximum</b>                                    | 1 600 V   |
| <b>service factor</b>   | 1   |
| <b>surge voltage resistance rated value</b>   | 6 kV  |
| <b>maximum permissible voltage for safe isolation</b>                               |   |
| • between main and auxiliary circuit  | 600 V   |
| <b>shock resistance</b>   | 15 g / 11 ms, from 12 g / 11 ms with potential contact lifting                  |
| <b>vibration resistance</b>   | 15 mm to 6 Hz; 2g to 500 Hz   |
| <b>utilization category acc. to IEC 60947-4-2</b>                                   | AC 53a  |
| <b>reference code acc. to IEC 81346-2</b>   | Q   |
| <b>Substance Prohibitance (Date)</b>  | 15.02.2018 00:00:00   |
| <b>product function</b>   |   |
| • ramp-up (soft starting)   | Yes   |
| • ramp-down (soft stop)   | Yes   |
| • Soft Torque   | Yes   |
| • adjustable current limitation   | Yes   |
| • pump ramp down  | Yes   |
| • intrinsic device protection   | Yes   |
| • motor overload protection   | Yes; Electronic motor overload protection                                       |
| • evaluation of thermistor motor protection   | No  |
| • inside-delta circuit  | Yes   |
| • auto-RESET  | Yes   |
| • manual RESET  | Yes   |
| • remote reset  | Yes; By turning off the control supply voltage                                  |
| • communication function  | Yes   |
| • operating measured value display  | Yes; Only in conjunction with special accessories                               |
| • error logbook   | Yes; Only in conjunction with special accessories                               |
| • via software parameterizable  | No  |
| • via software configurable   | Yes   |
| • <b>PROFInergy</b>   | Yes; in connection with the PROFINET Standard communication module              |
| • <b>firmware update</b>  | Yes   |
| • <b>removable terminal for control circuit</b>                                     | Yes   |
| • torque control  | No  |
| • analog output   | Yes; 4 ... 20 mA (default) / 0 ... 10 V (parameterizable with High Feature HMI) |
| <b>Power Electronics</b>  |   |
| <b>operational current</b>  |   |
| • at 40 °C rated value  | 38 A  |
| • at 50 °C rated value  | 34 A  |
| • at 60 °C rated value  | 31 A  |
| <b>operational current at inside-delta circuit</b>                                  |   |
| • at 40 °C rated value  | 65.8 A  |
| • at 50 °C rated value  | 58 A  |
| • at 60 °C rated value  | 52.8 A  |
| <b>operating voltage</b>  |   |
| • rated value   | 200 ... 600 V   |
| • at inside-delta circuit rated value   | 200 ... 600 V   |
| <b>relative negative tolerance of the operating voltage</b>                         | -15 %   |
| <b>relative positive tolerance of the operating voltage</b>                         | 10 %  |
| <b>relative negative tolerance of the operating voltage at inside-delta circuit</b> | -15 %   |

|   |         |
|---|---------|
| <b>relative positive tolerance of the operating voltage at inside-delta circuit</b> | 10 %    |
| <b>operating power for 3-phase motors</b>   |         |
| • at 230 V at 40 °C rated value   | 11 kW   |
| • at 230 V at inside-delta circuit at 40 °C rated value                             | 18.5 kW |
| • at 400 V at 40 °C rated value   | 18.5 kW |
| • at 400 V at inside-delta circuit at 40 °C rated value                             | 30 kW   |
| • at 500 V at 40 °C rated value   | 22 kW   |
| • at 500 V at inside-delta circuit at 40 °C rated value                             | 37 kW   |
| <b>Operating frequency 1 rated value</b>  | 50 Hz   |
| <b>Operating frequency 2 rated value</b>  | 60 Hz   |
| <b>relative negative tolerance of the operating frequency</b>                       | -10 %   |
| <b>relative positive tolerance of the operating frequency</b>                       | 10 %    |
| <b>adjustable motor current</b>   |         |
| • at rotary coding switch on switch position 1                                      | 15.5 A  |
| • at rotary coding switch on switch position 2                                      | 17 A    |
| • at rotary coding switch on switch position 3                                      | 18.5 A  |
| • at rotary coding switch on switch position 4                                      | 20 A    |
| • at rotary coding switch on switch position 5                                      | 21.5 A  |
| • at rotary coding switch on switch position 6                                      | 23 A    |
| • at rotary coding switch on switch position 7                                      | 24.5 A  |
| • at rotary coding switch on switch position 8                                      | 26 A    |
| • at rotary coding switch on switch position 9                                      | 27.5 A  |
| • at rotary coding switch on switch position 10                                     | 29 A    |
| • at rotary coding switch on switch position 11                                     | 30.5 A  |
| • at rotary coding switch on switch position 12                                     | 32 A    |
| • at rotary coding switch on switch position 13                                     | 33.5 A  |
| • at rotary coding switch on switch position 14                                     | 35 A    |
| • at rotary coding switch on switch position 15                                     | 36.5 A  |
| • at rotary coding switch on switch position 16                                     | 38 A    |
| • minimum   | 15.5 A  |
| <b>adjustable motor current</b>   |         |
| • for inside-delta circuit at rotary coding switch on switch position 1             | 26.8 A  |
| • for inside-delta circuit at rotary coding switch on switch position 2             | 29.4 A  |
| • for inside-delta circuit at rotary coding switch on switch position 3             | 32 A    |
| • for inside-delta circuit at rotary coding switch on switch position 4             | 34.6 A  |
| • for inside-delta circuit at rotary coding switch on switch position 5             | 37.2 A  |
| • for inside-delta circuit at rotary coding switch on switch position 6             | 39.8 A  |
| • for inside-delta circuit at rotary coding switch on switch position 7             | 42.4 A  |
| • for inside-delta circuit at rotary coding switch on switch position 8             | 45 A    |
| • for inside-delta circuit at rotary coding switch on switch position 9             | 47.6 A  |
| • for inside-delta circuit at rotary coding switch on switch position 10            | 50.2 A  |
| • for inside-delta circuit at rotary coding switch on switch position 11            | 52.8 A  |
| • for inside-delta circuit at rotary coding switch on switch position 12            | 55.4 A  |
| • for inside-delta circuit at rotary coding switch on switch position 13            | 58 A    |
| • for inside-delta circuit at rotary coding switch on switch position 14            | 60.6 A  |
| • for inside-delta circuit at rotary coding switch on switch position 15            | 63.2 A  |

|   |  |
|---|--|
| <ul style="list-style-type: none"> <li>• for inside-delta circuit at rotary coding switch on switch position 16</li> <li>• at inside-delta circuit minimum</li> </ul>                                     | 65.8 A<br>26.8 A   |
| <b>minimum load [%]</b>   | 15 %; Relative to smallest settable I <sub>e</sub>   |
| <b>power loss [W] for rated value of the current at AC</b> <ul style="list-style-type: none"> <li>• at 40 °C after startup</li> <li>• at 50 °C after startup</li> <li>• at 60 °C after startup</li> </ul> | 23 W<br>22 W<br>21 W   |
| <b>power loss [W] at AC at current limitation 350 %</b> <ul style="list-style-type: none"> <li>• at 40 °C during startup</li> <li>• at 50 °C during startup</li> <li>• at 60 °C during startup</li> </ul> | 628 W<br>526 W<br>464 W  |
| <b>Control circuit/ Control</b>   |  |
| <b>type of voltage of the control supply voltage</b>  | AC/DC  |
| <b>control supply voltage at AC</b> <ul style="list-style-type: none"> <li>• at 50 Hz rated value</li> <li>• at 60 Hz rated value</li> </ul>  | 24 V<br>24 V   |
| <b>relative negative tolerance of the control supply voltage at AC at 50 Hz</b>   | -20 %  |
| <b>relative positive tolerance of the control supply voltage at AC at 50 Hz</b>   | 20 %   |
| <b>relative negative tolerance of the control supply voltage at AC at 60 Hz</b>   | -20 %  |
| <b>relative positive tolerance of the control supply voltage at AC at 60 Hz</b>   | 20 %   |
| <b>control supply voltage frequency</b>   | 50 ... 60 Hz   |
| <b>relative negative tolerance of the control supply voltage frequency</b>  | -10 %  |
| <b>relative positive tolerance of the control supply voltage frequency</b>  | 10 %   |
| <b>control supply voltage</b> <ul style="list-style-type: none"> <li>• at DC rated value</li> </ul>   | 24 V   |
| <b>relative negative tolerance of the control supply voltage at DC</b>  | -20 %  |
| <b>relative positive tolerance of the control supply voltage at DC</b>  | 20 %   |
| <b>control supply current in standby mode rated value</b>   | 160 mA   |
| <b>holding current in bypass operation rated value</b>  | 360 mA   |
| <b>locked-rotor current at close of bypass contact maximum</b>  | 0.75 A   |
| <b>inrush current peak at application of control supply voltage maximum</b>   | 3.3 A  |
| <b>duration of inrush current peak at application of control supply voltage</b>   | 12.1 ms  |
| <b>design of the overvoltage protection</b>   | Varistor   |
| <b>design of short-circuit protection for control circuit</b>   | 4 A gG fuse (I <sub>cu</sub> =1 kA), 6 A quick-acting fuse (I <sub>cu</sub> =1 kA), C1 miniature circuit breaker (I <sub>cu</sub> = 600 A), C6 miniature circuit breaker (I <sub>cu</sub> = 300 A); Is not part of scope of supply |
| <b>Inputs/ Outputs</b>  |  |
| <b>number of digital inputs</b>   | 1  |
| <b>number of inputs for thermistor connection</b>   | 0  |
| <b>number of digital outputs</b> <ul style="list-style-type: none"> <li>• not parameterizable</li> </ul>  | 3<br>2   |
| <b>digital output version</b>   | 2 normally-open contacts (NO) / 1 changeover contact (CO)  |
| <b>number of analog outputs</b>   | 1  |
| <b>switching capacity current of the relay outputs</b> <ul style="list-style-type: none"> <li>• at AC-15 at 250 V rated value</li> <li>• at DC-13 at 24 V rated value</li> </ul>                          | 3 A<br>1 A   |
| <b>Installation/ mounting/ dimensions</b>   |  |
| <b>mounting position</b>  | with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back   |
| <b>fastening method</b>   | screw fixing   |

|  |   |
|--|---|
| <b>height</b>  | 275 mm  |
| <b>width</b>   | 170 mm  |
| <b>depth</b>   | 152 mm  |
| required spacing with side-by-side mounting                                  |   |
| • forwards   | 10 mm   |
| • backwards  | 0 mm  |
| • upwards  | 100 mm  |
| • downwards  | 75 mm   |
| • at the side  | 5 mm  |
| <b>weight without packaging</b>  | 2.3 kg  |
| <b>Connections/ Terminals</b>  |   |
| <b>type of electrical connection</b>   |   |
| • for main current circuit   | screw-type terminals  |
| • for control circuit  | spring-loaded terminals   |
| <b>type of connectable conductor cross-sections</b>                          |   |
| • for main contacts  |   |
| — solid  | 2x (1.0 ... 2.5 mm <sup>2</sup> ), 2x (2.5 ... 10 mm <sup>2</sup> )   |
| — finely stranded with core end processing                                   | 2x (1.0 ... 2.5 mm <sup>2</sup> ), 2x (2.5 ... 6.0 mm <sup>2</sup> )  |
| • at AWG cables for main current circuit solid                               | 2x (16 ... 12), 2x (14 ... 8)   |
| <b>type of connectable conductor cross-sections</b>                          |   |
| • for control circuit solid  | 2x (0.25 ... 1.5 mm <sup>2</sup> )  |
| • for control circuit finely stranded with core end processing               | 2x (0.25 ... 1.5 mm <sup>2</sup> )  |
| • at AWG cables for control circuit solid                                    | 2x (24 ... 16)  |
| • at AWG cables for control circuit finely stranded with core end processing | 2x (24 ... 16)  |
| <b>wire length</b>   |   |
| • between soft starter and motor maximum                                     | 800 m   |
| • at the digital inputs at AC maximum  | 100 m   |
| • at the digital inputs at DC maximum  | 1 000 m   |
| <b>tightening torque</b>   |   |
| • for main contacts with screw-type terminals                                | 2 ... 2.5 N·m   |
| • for auxiliary and control contacts with screw-type terminals               | 0.8 ... 1.2 N·m   |
| <b>tightening torque [lbf·in]</b>  |   |
| • for main contacts with screw-type terminals                                | 18 ... 22 lbf·in  |
| • for auxiliary and control contacts with screw-type terminals               | 7 ... 10.3 lbf·in   |
| <b>Ambient conditions</b>  |   |
| installation altitude at height above sea level maximum                      | 5 000 m; Derating as of 1000 m, see catalog   |
| <b>ambient temperature</b>   |   |
| • during operation   | -25 ... +60 °C; Please observe derating at temperatures of 40 °C or above   |
| • during storage and transport   | -40 ... +80 °C  |
| <b>environmental category</b>  |   |
| • during operation acc. to IEC 60721   | 3K6 (no ice formation, only occasional condensation), 3C3 (no salt mist), 3S2 (sand must not get into the devices), 3M6 |
| • during storage acc. to IEC 60721   | 1K6 (only occasional condensation), 1C2 (no salt mist), 1S2 (sand must not get inside the devices), 1M4                 |
| • during transport acc. to IEC 60721   | 2K2, 2C1, 2S1, 2M2 (max. fall height 0.3 m)   |
| <b>EMC emitted interference</b>  | acc. to IEC 60947-4-2: Class A  |
| <b>Communication/ Protocol</b>   |   |
| <b>communication module is supported</b>                                     |   |
| • PROFINET standard  | Yes   |
| • EtherNet/IP  | Yes   |
| • Modbus RTU   | Yes   |
| • Modbus TCP   | Yes   |
| • PROFIBUS   | Yes   |
| <b>UL/CSA ratings</b>  |   |

|  |  |  |  |  |   |
|--|--|--|--|--|---|
| manufacturer's article number  |  |  |  |  |   |
| <ul style="list-style-type: none"><li>● of circuit breaker<ul style="list-style-type: none"><li>— usable for Standard Faults at 460/480 V according to UL</li><li>— usable for High Faults at 460/480 V according to UL</li><li>— usable for Standard Faults at 460/480 V at inside-delta circuit according to UL</li><li>— usable for High Faults at 460/480 V at inside-delta circuit according to UL</li><li>— usable for Standard Faults at 575/600 V according to UL</li><li>— usable for Standard Faults at 575/600 V at inside-delta circuit according to UL</li></ul></li><li>● of the fuse<ul style="list-style-type: none"><li>— usable for Standard Faults up to 575/600 V according to UL</li><li>— usable for High Faults up to 575/600 V according to UL</li><li>— usable for Standard Faults at inside-delta circuit up to 575/600 V according to UL</li><li>— usable for High Faults at inside-delta circuit up to 575/600 V according to UL</li></ul></li></ul> | <p>Siemens type: 3RV2742, max. 70 A or 3VA51, max. 125 A; Iq = 5 kA</p> <p>Siemens type: 3RV2742, max.40 A or 3VA51, max. 60 A; Iq max = 65 kA</p> <p>Siemens type: 3RV2742, max. 70 A or 3VA51, max. 125 A; Iq = 5 kA</p> <p>Siemens type: 3VA51, max. 60 A; Iq max = 65 kA</p> <p>Siemens type: 3RV2742, max. 70 A or 3VA51, max. 125 A; Iq = 5 kA</p> <p>Siemens type: 3RV2742, max. 70 A or 3VA51, max. 125 A; Iq = 5 kA</p> |  |  |  |   |
| <b>operating power [hp] for 3-phase motors</b> <ul style="list-style-type: none"><li>● at 200/208 V at 50 °C rated value</li><li>● at 220/230 V at 50 °C rated value</li><li>● at 460/480 V at 50 °C rated value</li><li>● at 575/600 V at 50 °C rated value</li><li>● at 200/208 V at inside-delta circuit at 50 °C rated value</li><li>● at 220/230 V at inside-delta circuit at 50 °C rated value</li><li>● at 460/480 V at inside-delta circuit at 50 °C rated value</li><li>● at 575/600 V at inside-delta circuit at 50 °C rated value</li></ul>   | <p>10 hp</p> <p>10 hp</p> <p>20 hp</p> <p>30 hp</p> <p>15 hp</p> <p>20 hp</p> <p>40 hp</p> <p>50 hp</p>  |  |  |  |   |
| <b>contact rating of auxiliary contacts according to UL</b>  | R300-B300  |  |  |  |   |
| <b>Safety related data</b>   |  |  |  |  |   |
| <b>protection class IP on the front acc. to IEC 60529</b>  | IP20   |  |  |  |   |
| <b>touch protection on the front acc. to IEC 60529</b>   | finger-safe, for vertical contact from the front   |  |  |  |   |
| <b>electromagnetic compatibility</b>   | in accordance with IEC 60947-4-2   |  |  |  |   |
| <b>Certificates/ approvals</b>   |  |  |  |  |   |
| <b>General Product Approval</b>  | <b>EMC</b>   | <b>Declaration of Conformity</b>   |  |  |   |
| <br>CSA   | <br>CCC   | <br>UL                |         | <br>RCM | <br>EG-Konf. |
| <b>Test Certificates</b>   | <b>Marine / Shipping</b>   |  |  |  |   |
| <a href="#">Type Test Certificates/Test Report</a>   | <br>ABS   | <br>BUREAU<br>VERITAS | <br>LRS | <br>PRS | <br>DNV GL   |
| other  |  |  |  |  |   |

#### Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

<https://www.siemens.com/ic10>

Industry Mall (Online ordering system)

<https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RW5217-3AC05>

Cax online generator

<http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RW5217-3AC05>

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

<https://support.industry.siemens.com/cs/ww/en/ps/3RW5217-3AC05>

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

[http://www.automation.siemens.com/bilddb/cax\\_de.aspx?mlfb=3RW5217-3AC05&lang=en](http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RW5217-3AC05&lang=en)

Characteristic: Tripping characteristics, I<sup>2</sup>t, Let-through current

<https://support.industry.siemens.com/cs/ww/en/ps/3RW5217-3AC05/char>

Characteristic: Installation altitude

<http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RW5217-3AC05&objecttype=14&gridview=view1>

Simulation Tool for Soft Starters (STS)

<https://support.industry.siemens.com/cs/ww/en/view/101494917>

